

PRO+ Series X circuit breaker design chart

PRO+ Series X sulakemitoitustaulukko

				Number of luminaires per circuit breaker Kytettävien valaisimien enimmäismäärä			
				B10 A	B16 A	C10 A	C16 A
PRO+ 4X	290mA	99 W	0,45 A	13	21	20	32
	350mA	120 W	0,55 A	10	17	16	26
	420mA	146 W	0,67 A	9	14	13	21
PRO+ 6X	290mA	149 W	0,68 A	9	14	13	22
	350mA	180 W	0,82 A	7	12	11	18
	420mA	218 W	1,00 A	6	10	9	15
PRO+ 8X	290mA	198 W	0,91 A	6	11	10	16
	350mA	240 W	1,10 A	6	9	8	13
	420mA	286 W	1,31 A	4	7	7	11
PRO+ 12X	290mA	298 W	1,36 A	4	7	6	10
	350mA	360 W	1,65 A	3	5	5	8
	420mA	436 W	2,00 A	3	4	4	7

	Inrush current peak Käynnistysvirtapiikki	Earth leakage current Maavuotovirta
PRO+ 4X	< 4A (pulses greater than 1ms) 15A, t=170µs (10% of Ipeak)	0,58 mA
PRO+ 6X	< 4A (pulses greater than 1ms) 15A, t=170µs (10% of Ipeak)	0,61 mA
PRO+ 8X	< 4A (pulses greater than 1ms) 15A, t=170µs (10% of Ipeak)	0,69 mA
PRO+ 12X	< 8A (pulses greater than 1ms) 30A, t=170µs (10% of Ipeak)	1,15 mA